Product data sheet

Power connectors



Product description

RD30 female panel mount connector, Contacts: 4+PE, shielding is not possible, screw clamp, IP65, ESTI+, VDE

Area Order number RD30 series 694 99 0712 00 05







You can find the assembly instructions on the next page.

Technical data

General values

Connector design Connector locking system Termination Wire gauge (mm) Wire gauge (AWG) Upper limit temperature Lower limit temperature Customs tariff number Packaging Unit

Cable data

Approval 1 Approval 2 female panel mount connector screw screw clamp 2.50 mm² 14 100 °C - 40 °C 85369010 30

ESTI+ VDE

Electrical values

Rated current (40 °C) Rated voltage Rated impulse voltage Pollution degree Overvoltage category Insulating material group Insulation resistance EMC compliance Degree of protection Mechanical operation

Material

Contact material Contact plating Contact body material Housing material 20 A 400 V 6000 V 3 III III $\geq 10^{10} \Omega$ shielding is not possible IP65 > 500 Mating cycles

CuSn (bronze) Ag (silver) PA (UL94 HB) PA



Product data sheet

Power connectors



Product description

RD30 female panel mount connector, Contacts: 4+PE, shielding is not possible, screw clamp, IP65, ESTI+, VDE

Area Order number RD30 series 694 99 0712 00 05





Product data sheet

Power connectors



Product description

RD30 female panel mount connector, Contacts: 4+PE, shielding is not possible, screw clamp, IP65, ESTI+, VDE

Area Order number RD30 series 694 99 0712 00 05

Security notices

The connector must not be connected or separated under load. Non-observance and incorrect use can result in personal injury.

The connectors are designed for use in plant, control system and electrical equipment. The end user is responsible for checking whether the connectors are suitable for use in other applications.

The end user must take suitable safety measures to ensure that the connector cannot be disconnected accidentally. Connectors with degree of protection IP 67 and IP 68 are not suitable for use under water. When used outdoors, the connectors must be separately protected against corrosion. For further information about IP degrees of protection refer to 'Technical support' in the Download Centre.

